

LogiLink®

Universal Power Adapter 3–12 V

8 Changeable Tips Included

Art. No.: PA0167



Ideal as a replacement or secondary power adapter for electronics and small home appliance.

Features:

- » Provide different charger adapters for easily charging most of the digital devices
- » Reliable replacement or secondary power adapter in home or office
- » Built-in protection against overcurrent, overvoltage, over-temperature and short-circuit



Home/Office



For digital camera, battery chargers,
mobile phone, router, games console
and many others



Specification:

| | |
|-----------------------|---|
| Input Voltage | AC 100–240 V 50/60 Hz 0.6 A max. |
| Output Power | DC 3 V/4.5 V/5 V/6 V/7.5 V/9 V/ 12 V 1 A (12 W max.) |
| Efficiency | 78% max. |
| Standby Power Loss | ≤0.3 W |
| Operating Temperature | 0–45°C |
| Operating Humidity | 10–80% RH (no condensation) |
| Dimensions | 7.5 x 4.3 x 3.6 cm (without cable) |
| Weight | 0.105 kg |
| Cable Length | 1.5 m |
| DC Plug | 5.5 x 2.1 mm |



| | |
|------------------------|--------------|
| C | 5.5 x 2.5mm |
| H | 3.5 x 1.35mm |
| T | 3.5mm Jack |
| G | 4.0 x 1.7mm |
| L | 3.0 x 1.1mm |
| I | 2.5 x 0.7mm |
| S | Micro USB |
| LED Terminal Connector | |



*The specifications and pictures are subject to change without prior notice.
*All trade names referenced are the registered trademarks of their respective owners.



PA0167



4 052792 047875

Made in China

Package Contents:

- » 1 x Universal Power Adapter
- » 8 x Changeable Tips
- » 1 x Key
- » 1 x User Manual

Package Information:

- » Packing Dimension: 176 x 127.5 x 42 mm
- » Packing Weight: 0.2 kg
- » Carton Dimension: 515 x 265 x 370 mm
- » Carton Q'ty: 40 pcs
- » Carton Weight: 8.2 kg

**Warning**

- *For use with Information Technology Equipment.
- *Compare the specifications of your device with the specifications of the adapter. The power current (A) of your device should be equal to or lower than the power current of the power supply.
- *Only to be used indoor.
- *Only to be used after powering on.
- *Only to be used within max load.
- *Remove the power adapter from its power source after use.



*The specifications and pictures are subject to change without prior notice.
*All trade names referenced are the registered trademarks of their respective owners.



Made in China