

# **High Performance Outdoor Power Solution**

LogiLink's Portable Power Station is engineered to provide reusable, rechargeable portable power for a variety of applications. It is safe to use with built-in intelligent cooling system, multi-charging protections, eco-friendly and remotely controllable with app. Perfect for road trip, camping or during a power outage.







Solar Power



Car Charge



Fast Charge



Flashlight



Safe to Use



App Control



Easy to Transport

#### **Long Lasting & Safe Power Solution**

The durable, stable and efficient Lithium iron phosphate (LiFePO4) battery works with solar charging, supplying off-grid power to your needs.





### 9 Output Ports Can Be Used Simultaneously

Equipped with 9 charging output ports and it have 5 output modes of AC, USB, DC 5521 and car charger. Compatible with multiple electrical devices at the same time.





#### **Emergency LED Light**

4 brightness levels and SOS lighting ... to lit up the camping ground.

## Large & Clear LCD Display

Easy to read LCD display allows user to see the power supply quantity and charging efficiency at a glance.

#### 3 Charging Modes

Quick recharge through solar panel, AC or car.



Wall Charging



Car Charging



Charging

#### **Multiple Safety Protections**

Reliable with 8 kinds of security protections and make daily use more secure.



Undervoltage



Overvoltage



Overcurrent



Overload



Overtemperature



Cryogenic



Short Circuit



**SOH** Monitor

Compatible with LogiLink Foldable Solar Panels, Solar Cables and Cigarette Lighter to Alligator Clip Cable.



PHC0400/PHC0401

PVP0100/PVP0200

## Wireless Control with Tuya App

Remotely control or monitor the power usage, temperature and setup timer through the free *Smart Life* app.



Download the free APP from the App Store or Google Play store.

**Smart Life** 

#### **Specifications:**

Battery Type	LiFePO4
Battery Capacity	512 Wh, 25.6 V DC 20 Ah
Battery Life Cycle	3000 cycles
Wireless Standard	IEEE 802.11b/g/n
Wireless Technology	Wi-Fi
Wireless Frequency Range	2400–2483.5 MHz
Max. Transmission Power	97.27 mW
Inputs	AC: 220–240 V~, 50/60 Hz, 6 A (1200 W max.) Solar panel/Car input: 12–20 V/10 A (200 W max.)
Outputs	AC outputs x2: 220–240 V~, 50/60 Hz, 3 A (total 600 W max.) Car charger: 12.6 V/10 A (120 W max.) DC 5521 outputs x2: 12.6 V/3 A (36 W max.) Car Charger Output + DC 5521 Outputs: Total 126.0 W max. USB-A1/A2: 5 V/2.4 A (12 W max.) USB-C1/C2: 5 V/3 A (15 W), 9 V/3 A (27 W), 12 V/3 A (36 W), 15 V/3 A (45 W) 20 V/5 A (100 W max.)
Protections	Over temperature, low temperature, over-discharge, overcharge, overcurrent, overload and short circuit
IP Rating	IP20
Discharge Temperature	-20-45°C
Charge Temperature	0-45°C
Dimensions	30.1 x 22.7 x 19.3 cm
Weight	7 kg
AC Cable Length	1.5 m

#### **Package Contents:**

- » 1x Power Station
- » 1x AC Cable
- » 1x Car Charging Cable
- » 1x User Manual

#### **Package Information:**

» Packing Dimension: 380 x 308 x 314 mm

» Packing Weight: 9.15 kg

» Carton Dimension: 380 x 308 x 314 mm

» Carton Q'ty: 1 pc» Carton Weight: 9.15 kg





