

LogiLink_®

Remote Power Socket Set

2 x Indoor Sockets & 1 x Outdoor Socket & 1 x Remote Control

Art. No.: EC0009

Remotely turn your indoor and outdoor electrical appliances on and off with a convenient remote control any time. Make your life easier and more comfortable.

Indoor and Outdoor Use

Indoor and outdoor sockets are included in this kit. Simply plug them in and get started or synchronize the sockets according to your needs; provides stable connections without interference.

Outdoor Socket for IP44 Water Resistance

The durable and water resistant in green cover allows for use it in any weather. Great for the garden and patio.

Powerful Signal

Strong RF signal works through doors and walls without interfering with other electronics. It can transmit as far as 30 m.

Energy-Saving

Convenient control of electronics helps you reduce power consumption to save costs on electricity and extend the life of your devices and appliances.





Ш













LogiLink_®

Remote Power Socket Set

2 x Indoor Sockets & 1 x Outdoor Socket & 1 x Remote Control

Art. No.: EC0009

Specifications:

Voltage	230 V, 50 Hz
Maximum Power	16 A, 3680 W
Remote Control Battery	CR2032 3 V
Remote Frequency	433.92 MHz
Max. Transmission Power	1 mW
Transmission Range	Up to 30 m
Waterproof	IP44 (outdoor socket)
Dimensions	Indoor Socket: 55 x 72 x 92 mm Outdoor Socket: 57 x 85 x 105 mm Remote Control: 44 x 17 x 78 mm
Weight	Indoor Socket: 85 g Outdoor Socket: 112 g Remote Control: 30 g









Package Contents:

- » 2 x Indoor Sockets
- » 1 x Outdoor Socket
- » 1 x Remote Control
- » 1 x Button Cell CR2032
- » 1 x User Manual

Package Information:

» Packing Dimension: 158 x 107 x 61 mm

» Packing Weight: 0.3725 kg

» Carton Dimension: 335 x 235 x 350 mm

» Carton Q'ty: 20 pcs » Carton Weight: 7.05 kg





^{*}Do not operate under cover.

^{*}The specifications and pictures are subject to change without prior notice.
*All trade names referenced are the registered trademarks of their respective owners.







^{*}Voltage-free only when plug is disconnected.