

LogiLink

Energy Cost Meter

Art. No.: EM0002B

Spot the inefficient electrical equipment in your household with the LogiLink Energy Cost Meter. The display shows the energy and power needed. With inserting your personal power tariff it automatically calculates the cost tariff.

Features:

- » Measures power consumption and calculates energy costs
- » Easy to read with large LCD display
- » Load capacity up to 3600 W that you can easily connect any home device
- » Display power watts, mains voltage, energy consumption, energy costs and overload warning
- » Programmable power tariffs
- » Data is automatically stored when power failure happens
- » Suitable for a wide range of devices such as computers, gaming consoles, printers, TVs, set-top boxes, routers, and others
- » With safety shutter







*The specifications and pictures are subject to change without prior notice. *All trade names referenced are the registered trademarks of their respective owners.

Made in China

052792

Specification:

Rated Voltage	230 V AC 50 Hz
Maximum Load	16 A, 3600 W
Standby Power Consumption	0.3 W
Type of Plug	Safety plug CEE 7/4
Type of Socket	German socket CEE 7/3
LCD Display	1.9" LCD
Function Buttons	MODE, SET, RESET
Power Display	0.0-9999 W
Voltage Display	0.0-9999 V
Electricity Tariffs Display	0.00–99.99 Cost/kWh
Accumulated Electricity Display	0.00–9999 Cost
Total Energy Consumption Display	0.00–9999 kWh
Overload Display	Yes
Protection Class	IP20
Safety Shutter	Yes
Measurement Deviation (Accuracy)	±1 %
Currency Display	€
Operating Temperature	-10-40°C
Operating Humidity	0–93% RH (non-condensing)
Product Dimensions	10.8 x 5.7 x 7.63 cm
Weight	0.108 kg
Color	White

Package Contents:

- » 1x Energy Cost Meter
- » 1x User Manual

Package Information:

- » Packing Dimension: 82 x 61 x 111 mm
- » Packing Weight: 0.152 kg
- » Carton Dimension: 350 x 330 x 365 mm
- » Carton Q'ty: 60 pcs
- » Carton Weight: 10.5 kg







