



App Remote Control

Smart Wall Switch can be controlled through your existing Wi-Fi network via the free *Smart Life* or *Megos Smart Home* app.





Smart Life

Megos Smart Home

Download the free APP from the App Store or Google Play store.















Discrete and Convenient

Simplicity design blends into your room's interior. Can operate as traditional wall switch or remotely or automatically.



Control Your Lights from Anywhere

Turn on/off or schedule lighting wherever you are through your smartphone at any time. Helping you to save energy and electricity bills.

Families can share light switches. You can easily add other family members and control the same device together.



Works with Amazon Alexa and Google Home

Manage your home devices through voice control to make your life effortless.

Specifications:

Wireless Standard	IEEE 802.11b/g/n
Wireless Frequency Range	2,412–2,472 MHz
Max. Transmission Power	34.914 mW
Max. Transmit Antenna Gain	3 dBi
Rated Voltage	AC 230 V 50 Hz, 10 A
Output Power	1000 W (500 W/channel)
Output Current	4.54 A
Max. Power Consumption	1.8 W
Device Power Output Connection	Terminal block
Mounting	Flush mount
Internal Deptch	26 mm
Hole Spacing, Mounting Plate	60 mm
Operating Mode	Touch sensitive
LED Indicator	Blue when switch is turned on
Operation Distance (In Open Area)	Up to 45 m
Number of Switching Cycles	100000 switch cycles
Material	PC, tempered glass
Operating Temperature	-20–45°C
Operating Humidity	20-85% RH (non-condensing)
Color	White
Product Dimension	8.6 x 8.6 x 3.4 cm
System Requirements	Android 5 or above / iOS 11 or above

Package Contents:

- » 1x Smart Dual Wall Switch
- » 1x User Manual

Package Information:

» Packing Dimension: 115 x 50 x 145 mm

» Packing Weight: kg » Carton Dimension: mm

» Carton Q'ty: pcs » Carton Weight: kg





